

**EKI-7526MI**

**16+2 100 FX Port Unmanaged  
Industrial Ethernet Switch**

**User Manual**

## **Copyright**

The documentation and the software included with this product are copyrighted 2009 by Advantech Co., Ltd. All rights are reserved. Advantech Co., Ltd. reserves the right to make improvements in the products described in this manual at any time without notice. No part of this manual may be reproduced, copied, translated or transmitted in any form or by any means without the prior written permission of Advantech Co., Ltd. Information provided in this manual is intended to be accurate and reliable. However, Advantech Co., Ltd. assumes no responsibility for its use, nor for any infringements of the rights of third parties, which may result from its use.

## **Acknowledgements**

Intel and Pentium are trademarks of Intel Corporation.  
Microsoft Windows and MS-DOS are registered trademarks of Microsoft Corp.  
All other product names or trademarks are properties of their respective owners.

## **Product Warranty (2 years)**

Advantech warrants to you, the original purchaser, that each of its products will be free from defects in materials and workmanship for two years from the date of purchase.

This warranty does not apply to any products which have been repaired or altered by persons other than repair personnel authorized by Advantech, or which have been subject to misuse, abuse, accident or improper installation. Advantech assumes no liability under the terms of this warranty as a consequence of such events.

Because of Advantech's high quality-control standards and rigorous testing, most of our customers never need to use our repair service. If an Advantech product is defective, it will be repaired or replaced at no charge during the warranty period. For out-of-warranty repairs, you will be billed according to the cost of replacement materials, service time and freight. Please consult your dealer for more details.

If you think you have a defective product, follow these steps:

1. Collect all the information about the problem encountered. (For example, CPU speed, Advantech products used, other hardware and software used, etc.) Note anything abnormal and list any onscreen messages you get when the problem occurs.
2. Call your dealer and describe the problem. Please have your manual, product, and any helpful information readily available.
3. If your product is diagnosed as defective, obtain an RMA (return merchandise authorization) number from your dealer. This allows us to process your return more quickly.
4. Carefully pack the defective product, a fully-completed Repair and Replacement Order Card and a photocopy proof of purchase date (such as your sales receipt) in a shippable container. A product returned without proof of the purchase date is not eligible for warranty service.
5. Write the RMA number visibly on the outside of the package and ship it prepaid to your dealer.

## **Declaration of Conformity**

### **CE**

This product has passed the CE test for environmental specifications. Test conditions for passing included the equipment being operated within an industrial enclosure. In order to protect the product from being damaged by ESD (Electrostatic Discharge) and EMI leakage, we strongly recommend the use of CE-compliant industrial enclosure products.

### **FCC Class A**

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

## **Technical Support and Assistance**

- Step 1. Visit the Advantech web site at [www.advantech.com/support](http://www.advantech.com/support) where you can find the latest information about the product.
  
- Step 2. Contact your distributor, sales representative, or Advantech's customer service center for technical support if you need additional assistance. Please have the following information ready before you call:
  - Product name and serial number
  - Description of your peripheral attachments
  - Description of your software (operating system, version, application software, etc.)
  - A complete description of the problem
  - The exact wording of any error messages

## Safety Instructions

1. Read these safety instructions carefully.
2. Keep this User's Manual for later reference.
3. Disconnect this equipment from any AC outlet before cleaning. Use a damp cloth. Do not use liquid or spray detergents for cleaning.
4. For plug-in equipment, the power outlet socket must be located near the equipment and must be easily accessible.
5. Keep this equipment away from humidity.
6. Put this equipment on a reliable surface during installation. Dropping it or letting it fall may cause damage.
7. The openings on the enclosure are for air convection. Protect the equipment from overheating. **DO NOT COVER THE OPENINGS.**
8. Make sure the voltage of the power source is correct before connecting the equipment to the power outlet.
9. Position the power cord so that people cannot step on it. Do not place anything over the power cord.
10. All cautions and warnings on the equipment should be noted.
11. If the equipment is not used for a long time, disconnect it from the power source to avoid damage by transient overvoltage.
12. Never pour any liquid into an opening. This may cause fire or electrical shock.
13. Never open the equipment. For safety reasons, the equipment should be opened only by qualified service personnel.
14. If one of the following situations arises, get the equipment checked by service personnel:
  - a. The power cord or plug is damaged.
  - b. Liquid has penetrated into the equipment.
  - c. The equipment has been exposed to moisture.
  - d. The equipment does not work well, or you cannot get it to work according to the user's manual.
  - e. The equipment has been dropped and damaged.
  - f. The equipment has obvious signs of breakage.
15. **DO NOT LEAVE THIS EQUIPMENT IN AN ENVIRONMENT WHERE THE STORAGE TEMPERATURE MAY GO BELOW -40°C (-40°F) OR ABOVE 85°C (185°F). THIS COULD DAMAGE THE EQUIPMENT. THE EQUIPMENT SHOULD BE IN A CONTROLLED ENVIRONMENT.**

## **Safety Precaution - Static Electricity**

Follow these simple precautions to protect yourself from harm and the products from damage.

1. To avoid electrical shock, always disconnect the power from your PC chassis before you work on it. Don't touch any components on the CPU card or other cards while the PC is on.
2. Disconnect power before making any configuration changes. The sudden rush of power as you connect a jumper or install a card may damage sensitive electronic components.

# Contents

<b>Chapter 1</b>	<b>Overview</b>	<b>2</b>
1.1	Introduction	2
1.1.1	High-Speed Transmissions	2
1.1.2	Dual Power Input	2
1.1.3	Flexible Mounting	2
1.1.4	Advanced Protection	2
1.1.5	Wide Operating Temperature	2
1.1.6	Easy Troubleshooting	2
1.2	Features	3
1.3	Specification	4
1.4	Packing List	6
1.5	Safety Precaution	6
<b>Chapter 2</b>	<b>Installation</b>	<b>8</b>
2.1	LED Indicators	8
	Table 2.1: EKI-7526MI LED Definition	8
2.2	Dimensions (units: mm)	9
	Figure 2.1: Front View of EKI-7526MI	9
	Figure 2.2: Side View of EKI-7526MI	10
	Figure 2.3: Rear View of EKI-7526MI	11
	Figure 2.4: Top View of EKI-7526MI	11
2.3	Mounting	12
2.3.1	Wall mounting	12
	Figure 2.5: Combine the Metal Mounting Kit	12
2.3.2	DIN-rail Mounting	13
	Figure 2.6: Installation to DIN-rail Step 1	13
	Figure 2.7: Installation to DIN-rail Step 2	14
2.4	Network Connection	15
2.5	Power Connection	15
	Figure 2.8: Pin Assignment of the Power Connector	15
<b>Chapter 3</b>	<b>Troubleshooting</b>	<b>17</b>
<b>Appendix A</b>	<b>Pin Assignment &amp; Wiring</b>	<b>19</b>
	Figure A.1: RJ-45 Pin Assignment	19
	Figure A.2: EIA/TIA-568B	19
	Figure A.2: EIA/TIA-568A	19





## Overview

Sections include:

- Introduction
- Features
- Specifications
- Packing List
- Safety Precaution

# Chapter 1 Overview

## 1.1 Introduction

---

Aside from 16 x 10/100Base-TX fast Ethernet ports, the EKI-7526MI comes equipped with 2 100 Mbps fiber expansion ports. Also, the long MTBF (Mean Time Between Failures) ensures that the EKI-7526MI is a cost-effective solution and meets the high reliability requirements demanded by industrial applications.

### 1.1.1 High-Speed Transmissions

The EKI-7526MI includes a switch controller that can automatically sense transmission speeds (10/100 Mbps). The RJ-45 interface can also be auto-detected, so MDI or MDI-X is automatically selected and a crossover cable is not required. All Ethernet ports have memory buffers that support the store-and-forward mechanism. This assures that data is properly transmitted.

### 1.1.2 Dual Power Input

EKI-7526MI redundant power input design is with power reserve protection to prevent the switch device broken by wrong power wiring. When one of power input is fail, P-Fail LED will turn on and send an alarm through a relay output for notifying user.

### 1.1.3 Flexible Mounting

EKI-7526MI is extremely compact (79 x 152 x 105 mm) and can be mounted on a DIN-rail or a panel, so it is suitable for any space-constrained environment.

### 1.1.4 Advanced Protection

EKI-7526MI supports up to 3,000 V<sub>DC</sub> EFT protection for power line, and also supports 4,000V<sub>DC</sub> ESD protection for Ethernet ports. With these 2 strong protections, it can secure equipment against unregulated voltage and make systems safer and more reliable. Further, EKI-7526MI provides currency overload protection with a resettable fuse to ensure that the device component won't be damaged by overload current.

### 1.1.5 Wide Operating Temperature

The operating temperature of the EKI-7526MI is between -40 ~ 75 °C. With such a wide range, you can use the EKI-7526MI in some of the harshest industrial environments that exist.

### 1.1.6 Easy Troubleshooting

LED indicators make troubleshooting quick and easy. Each 10/100 Base-TX port has 2 LEDs that display the link status, transmission speed and collision status. Also the three power indicators P1, P2 and P-Fail help you diagnose immediately.

## 1.2 Features

---

- Provides 16 x 10/100 Mbps Ethernet ports with RJ45 connector
- Provides 2 100 Mbps fiber ports device
- Supports full/half duplex flow control
- Supports store and forward transmission
- Supports auto-negotiation
- Supports MDI/MDI-X auto crossover
- Provides broadcast storm protection
- Supports surge protection (EFT) 3,000 V<sub>DC</sub> for power line
- Supports 4,000 V<sub>DC</sub> ESD protection for Ethernet
- Supports +12 ~ 48 V<sub>DC</sub> power input
- Provides flexible mounting: DIN-rail, Wall Mounting
- Supports Wide range operating temperature from -40 ~ 75 °C (EKI-7526MI)

## 1.3 Specification

---

### Communications

<b>Compatibility</b>	IEEE 802.3, 802.3u, 802.3x
<b>LAN</b>	10/100Base-TX, 100Base-FX
<b>Transmission Distance</b>	Ethernet : Up to 100 m (Cat.5e, Cat.6 RJ-45 cable suggested for Gigabit port) Fiber : Multi-mode: Up to 2Km
<b>Transmission Speed</b>	Ethernet : Up to 100 Mbps Fiber : Up to 100 Mbps

### Interface

<b>Connectors</b>	16 x RJ-45 2 x Fiber 6-pin removable screw terminal (power & relay)
<b>LED Indicators</b>	Unit: PWR1, PWR2, P-Fail TX port: Link/Active, Duplex/Collision FX port: Link/Active

### Power

<b>Power Consumption</b>	Max. 8.9 Watts
<b>Power Input</b>	2 x Unregulated +12 ~ 48 V <sub>DC</sub>
<b>Fault Output</b>	1 Relay Output
<b>Inrush Current</b>	200% @ 24V <sub>DC</sub>

### Mechanism

<b>Dimensions (WxHxD)</b>	79 x 152 x 105 mm
<b>Enclosure</b>	IP30, Metal shell with solid mounting kits
<b>Mounting</b>	DIN-rail, Wall

### Protection

<b>ESD (Ethernet)</b>	4,000 V <sub>DC</sub>
<b>Surge (EFT for power)</b>	3,000 V <sub>DC</sub>

### Environment

<b>Operating Temperature</b>	-40 ~ 75 °C
<b>Operating Humidity</b>	5% ~ 95% (non-condensing)

**Storage Temperature**  
**MTBF**

-40 ~ 85 °C  
218490 hours

## Certifications

**Safety**

UL 508\*, Class 1 Division 2\*

**EMC**

U.S.A.: FCC Part 15 CISPR 22  
EU: EN55011  
EN55022  
EN61000-3-2/3  
EN55024  
IEC61000-4-2/3/4/5/6/8  
EN61000-6-2/4

**Free Fall**  
**Shock**  
**Vibration**

IEC60068-2-32  
IEC60068-2-27  
IEC60068-2-6

\* Future Release

## 1.4 Packing List

---

- 1 x EKI-7526MI 16+2 100FX Port Unmanaged Industrial Ethernet Switch
- 1 x eAutomation Industrial Communication CD-ROM with User manual
- 2 x Wall Mounting Bracket and Screws
- 1 x DIN-rail Mounting Bracket and Screws
- 1 x EKI-7526MI Startup Manual
- 1 x DC Jack Cable 2.0/150mm

## 1.5 Safety Precaution

---

*Attention*     *IF DC voltage is supplied by an external circuit, please use a protection device on the power supply input.*

## **Installation**

Sections include:

- LED Indicators
- Dimensions
- Mounting
- Network Connection
- Fiber Optic Network Connection
- Power Connection

## Chapter 2 Installation

In this chapter, you will be given an overview of the EKI-7526MI hardware installation procedures.

### 2.1 LED Indicators

---

There are few LEDs display the power status and network status located on the front panel of EKI-7526MI, each of them has its own specific meaning as the table below.

<i>Table 2.1: EKI-7526MI LED Definition</i>			
LED	Color	Description	
PWR1	Green	On	Power input 1 is active
		Off	Power input 1 is inactive
PWR2	Green	On	Power input 2 is active
		Off	Power input 2 is inactive
P-Fail	Red	On	Power input 1 or 2 is inactive
		Off	Power input 1 and 2 are both active, or no power input
Link/Active (17, 18)	Green	On	Connected to 100 Mbps network
		Flashing	Data is transmitting or receiving
		Off	Not connected to 100 Mbps network
Link/Active (1~16)	Green	On	Connected to network
		Flashing	Networking is active
		Off	Not connected to network
Duplex/Collision (1~16)	Yellow	On	Ethernet port full duplex
		Flashing	Collision of packets occurs
		Off	Ethernet port half duplex or not connect to network



## 2.2 Dimensions (units: mm)

---




Figure 2.1: Front View of EKI-7526MI




Figure 2.2: Side View of EKI-7526MI




Figure 2.3: Rear View of EKI-7526MI

Please refer to page 19 for pin assignment.




Figure 2.4: Top View of EKI-7526MI

## 2.3 Mounting


---

The EKI-7526MI supports two mounting methods: DIN-rail & Wall.

### 2.3.1 Wall mounting

EKI-7526MI can be wall-mounted by using the included mounting kit. Then, hang on the EKI-7526MI to the nails on the wall.

First, use the screws included in the package to combine the EKI-7526MI and metal mounting kit. And then you can install the device firmly via the components, please see Figure 2.5 as below.



*Figure 2.5: Combine the Metal Mounting Kit*

### 2.3.2 DIN-rail Mounting

You can also mount EKI-7526MI on a standard DIN-rail by below steps.

The DIN-rail kit is screwed on the industrial switch when out of factory. If the DIN-rail kit is not screwed on the industrial switch, please screw the DIN-rail kit on the switch first.

First, hang the EKI-7526MI to the DIN-rail with angle of inclination. See figure 2.6.



*Figure 2.6: Installation to DIN-rail Step 1*

Then, let the device down straight to slide over the rail smoothly. See Figure 2.7



*Figure 2.7: Installation to DIN-rail Step 2*

## 2.4 Network Connection

---

The EKI-7526MI has 16 x RJ-45 ports that support connection to 10 Mbps Ethernet, or 100 Mbps Fast Ethernet, and half or full duplex operation. EKI-7526MI can be connected to other hubs or switches via a twisted-pair straight-through or crossover cable up to 100m long. The connection can be made from any TX port of EKI-7526MI (MDI-X) to another hub or switch either MDI-X or uplink MDI port. Besides, EKI-7526MI provides 2 x SC type fiber ports for long distance uplinks up to 30km (single mode).

EKI-7526MI supports auto-crossover to make networking more easy and flexible. You can connect any RJ-45 (MDI-X) port on the switch to any device such as a switch, bridge or router.

## 2.5 Power Connection

---

The EKI-7526MI supports dual +12 ~48 V<sub>DC</sub> power inputs and power-fail relay output.




Figure 2.8: Pin Assignment of the Power Connector

You can connect an alarm indicator, buzzer or other signaling equipment through the relay output. The relay opens if power input 1 or 2 fails ('Open' means if you connect relay output with an LED, the light would be off).

CHAPTER  
**3**

# Troubleshooting



## Chapter 3 Troubleshooting

### 1. Power Input

Verify that is using the right power cord/adaptor 48 V<sub>DC</sub>, please don't use the power adaptor with DC output voltage higher than 48V, or it will burn this converter down.

### 2. Cable

Select the proper UTP cable to construct user network. Please check that is using the right cable. Use Unshielded Twisted-Pair (UTP) or Shielded Twisted-Pair (STP) cable for RJ-45 connections: 100 Category 3, 4 or 5 cable for 10 Mbps connections or 100 Category 5 cable for 100 Mbps connections. Also, be sure that the length of any twisted-pair connection does not exceed 100 meters (328 feet).

### 3. Diagnosing LED Indicators

The switch can be easily monitored through panel indicators, which describes common problems user may encounter and where user can find possible solutions, to assist in identifying.

If the power indicator does not light up when the power cord is plugged in, user may have a problem with power cord. Then check for loose power connections, power losses or surges at power outlet. If user still cannot resolve the problem, contact the local dealer for assistance.

If the Industrial switch LED indicators are normal and the connected cables are correct but the packets still cannot transmit, please check your system's Ethernet devices configuration or status.

APPENDIX  
**A**

# **Pin Assignment & Wiring**

# Appendix A Pin Assignment & Wiring

It is suggested to adopt ELA/TIA as the wiring of the RJ-45.




Figure A.1: RJ-45 Pin Assignment




Figure A.2: EIA/TIA-568B




Figure A.2: EIA/TIA-568A