

User's Note

For MIC-3355 User's Manual

Please update the J3 connector pin assignments according to the following table:

Pin	A	B	C	D	E
19	IDE2D3	IDE2D6	IDE2D2	IDE2D10	IDE2D14
18	IDE2D8	IDE2D5	IDE2D1	IDE2D11	IDE2D15
17	IDE2D9	IDE2D4	IDE2D0	IDE2D12	IDE2D13
16	IDE2D7	IDE2CS0-	IDE2IOR-	IDE2CS1-	IDE2RDY
15	IDE2DRQ	IDE2ACK-	IDE2SA2	IDE2IRQ	IDE2IOW-
14	GND	GND	IDE2SA1	GND	IDE2SA0
13	GND	GND	GND	GND	GND
12	IDE1D0	IDE1D2	IDE1D4	IDE1D7	GND
11	IDE1D1	IDE1D3	IDE1D8	IDE1D6	IDE1D12
10	IDE1D5	IDE1D9	IDE1D10	IDE1D11	IDE1D13
9	IDE1D15	IDE1D14	IDE1DRQ-	IDE1CS1-	IDE1IOR-
8	IRQ14	IDE1ACK-	N/C	IDE1SA2	IDE1IOW-
7	IDE1LED	GND	IDE1RST-	IDE1RDY	IDE1CS0-
6	GND	GND	GND	IDE1SA0	IDE1SA1
5	GND	GPIO5	IOCHK-	SDCLK1	SDDAT1
4	N/C	GND	GND	N/C	GND
3	DSKCHG-	MOTEA-	STEP-	SIDE1-	TK00-
2	DRVA-	MOTEB-	DVSL-	RDATA-	WPT-
1	INDEX-	DRVB-	FDIR-	WGATE-	WDATA-

Part No. 2003335501