
PCL-728

Isolated 2-ch D/A Output Card



Features

- · 2 independent, double-buffered 12-bit D/A output channels
- · Multiple output ranges:

0 ~ +5 V (unipolar) 0 ~ +10 V (unipolar)

±5 V (bipolar)

±10 V (bipolar)

4 ~ 20 mA (sink)

0 ~ 20 mA (sink)

- · Over 500 VDC isolation between input and output
- · 2 DB-9 connectors for easy wiring

Introduction

The PCL-728 provides two double-buffered 12-bit digital-to-analog outputs. Optical isolators give 500 volts of isolation (channel-to-channel and inputto-output) to protect the card and your PC from dangerous voltage on the output lines. You can output in several ranges: 0 to +5 V, 0 to +10 V, ±5 V, ±10 V, 0 to 20 mA (sink) or 4 to 20 mA (sink).

The PCL-728's register format and software driver are fully compatible with the PCL-726 6-channel D/A card. This makes it easy for you to replace the PCL-726 with the PCL-728 to gain immediate isolation protection.

Applications

- · Process control
- · Programmable voltage source
- · Programmable current sink
- · Servo control

Specifications

• Channels: 2 isolated D/A output channels

• Resolution: 12 bits, double buffered

• Output Range:

Unipolar: $0 \sim +5 \text{ V}$, $0 \sim +10 \text{ V}$

Bipolar: ±5 V, ±10 V

Current loop (sink): 0~ 20 mA, 4 ~ 20 mA

• Throughput: 17 KHz

• Settling Time: ≤ 60 µsec.

• Accuracy: ±0.012% full scale range

Isolation Voltage:

 $> 500\ V_{\text{DC}}$ channel-to-channel and input-to-output

• Temperature Drift: 5 PPM/° C (0° ~ 50° C)

• Reference Voltage:

Internal: -5 V or -10 V

External: ±10 V (max.), AC or DC

• Output Current: ±5 mA max.

• Current Loop Excitation Voltage: 8 ~ 36 V

• Power Consumption: +5 V @ 800 mA max.

• Operating Temperature: 0° ~ 50° C (32° ~ 122° F)

• Storage Temperature: 0° ~ 65° C (32° ~ 149° F)


Operating Humidity: 5% ~ 95% RH non-condensing

(refer to IEC 68-2-3)

• Connectors: two DB-9 connectors

• Dimensions: 184 mm (L) x 119 mm (H) (7.25" x 4.7")

Pin Assignment



Ordering Information

PCL-728: Isolated 2-channel D/A output card, user's manual and driver CD-ROM (cable not included)

WebOIT

IPPC &

ADAM-

4000

8000

VBOX