



### 3. Jumper J1: Power Type Select (reserved)

J1	
open	ATX
closed*	AT

\* Default setting: closed

The PCA-6114P10-B can also support 3.3V power. If 3.3V power is needed while using an AT power supply, please contact Advantech sales for customization.

### 4. PCI Routing Table

Primary PCI Group					
PCI Slot	IDSEL	PCI interrupt Pin Route			
		INTA	INTB	INTC	INTD
PPCI1	P_AD31	INTB	INTC	INTD	INTA
PPCI2	P_AD30	INTC	INTD	INTA	INTB
PPCI3	P_AD29	INTD	INTA	INTB	INTC6

Secondary PCI Group					
PCI Slot	IDSEL	PCI interrupt Pin Route			
		INTA	INTB	INTC	INTD
SPCI1	P_AD20	INTA	INTB	INTC	INTD
SPCI2	P_AD21	INTB	INTC	INTD	INTA
SPCI3	P_AD22	INTC	INTD	INTA	INTB
SPCI4	P_AD23	INTD	INTA	INTB	INTC

### 5. Detachable Board

Depending on chassis usage, users may need to remove the detachable board along the dotted lines.