

# Statement of Conformity

## Best Laboratory Co., Ltd.

No. 336, Ba Lian RD., Sec. 1, Hsi Chih City, Taipei Hsien, Taiwan, R.O.C.

Telephone: 886-2-2646-2899 Facsimile: 886-2-2646-2870

### *EMC Certificate*

**Applicant** : Advantech Co., Ltd.  
**Address** : Fl.4, No. 108-3, Ming-Chuan Road,  
Shing-Tien City, Taipei, Taiwan, R.O.C.  
**Equipment** : 5U-high Rackmount Chassis  
w/ backplane and power supply  
**Model** : CT-500 Series

Has fully complied with the requirements set out in the council directive on the approximation of the law of the members states relating to Electromagnetic Compatibility Directive (89/336/EEC). For the evaluation regarding EMC, the following standards were applied:

EMI: EN 50081-2:1993 -> EN 55011:1999, EN 61000-3-2:2000, EN 61000-3-3:1995


EMS: EN 61000-6-2:1999 -> EN 61000-4-2:1998, EN 61000-4-3:1998,  
EN 61000-4-4:1995, EN 61000-4-5:1995,  
EN 61000-4-6:1996, EN 61000-4-8:1993,  
EN 61000-4-11:1994,

**The date of the measurement: Aug. 22, 2002**

**The date of the certification signed: Aug. 24, 2002**

**The number of EMC Certificate: CER-A01-CE-822**

Test Laboratory

  
Quality Department Manager: JEFF CHIU



This verification is based on a single evaluation of one sample of above-mentioned products. It does not imply any assessment of the whole production and does not permit the use of the logo of the test laboratory.

# EMC TEST REPORT

Applicant : Advantech Co., Ltd.  
Equipment : 5U-high Rackmount Chassis  
w/ backplane and power supply  
Model : CT-500 Series

# Test Report Certification

## Best Laboratory Co., Ltd.

No. 336, Ba Lian Rd., Sec. 1, Hsi Chih City, Taipei Hsien, Taiwan, R.O.C.  
Tel: 886-2-2646-2899 Fax: 886-2-2646-2870

Applicant : Advantech Co., Ltd.

Address : Fl.4, No. 108-3, Ming-Chuan Road,  
Shing-Tien City, Taipei, Taiwan, R.O.C.

Equipment : 5U-high Rackmount Chassis w/ backplane and power supply

Model : CT-500 Series

Device's Class : Class A Device

Measurement Standard : EN 50081-2/1993, EN 61000-6-2/1999

Measurement Procedure : EN 55011/1999, EN 61000-3-2/2000, EN 61000-3-3/1995  
EN 61000-4-2/1998, EN 61000-4-3/1998, EN 61000-4-4/1995,  
EN 61000-4-5/1995, EN 61000-4-6/1996, EN 61000-4-8/1993  
EN 61000-4-11/1994

Operating Voltage : 230VAC, 50Hz

Test Result : **Compliance** (Detail showed in the test report)

Sample Received : Aug. 12, 2002

Test Date : Aug. 22, 2002

Report Number : RE-A01-CE-822

Test Firm : No. 336, Ba Lian Rd., Sec. 1,  
Hsi Chih City, Taipei Hsien, Taiwan, R.O.C.

Remark:

- (1) The test report is only relating to the sample tested
- (2) The test report shall not be reproduced except in full, without the written approval of Best Laboratory Co., Ltd.
- (3) The test result of this report are traceable to the national or international standards.

Prepared : IVAN HSIEH  
IVAN HSIEH

Approved : JEFF CHIU ( Title: Quality Department Manager )  
JEFF CHIU

Date Issued : Aug. 24, 2002

# Contain

- 1 General Information**
- 1.1 EUT Description.....4
- 1.2 Test System Detail.....5
- 1.3 Tested Configuration.....8
- 1.4 EUT Exercise Software.....9
- 1.5 Test Performed.....9
- 2 Conducted Emission Measurement at Mains Port**
- 2.1 Test Equipment List.....10
- 2.2 Test Set-Up.....10
- 2.3 Limit .....10
- 2.4 Test Procedure.....11
- 2.5 Test Specification.....11
- 2.6 Test Result.....11
- 3 Conducted Emission Measurement at Telecommunication Port**
- 3.1 Test Equipment List.....12
- 3.2 Test Set-Up.....12
- 3.3 Limit .....12
- 3.4 Test Procedure.....13
- 3.5 Test Specification.....13
- 3.6 Test Result.....13
- 4 Radiated Emission Measurement**
- 4.1 Test Equipment List.....14
- 4.2 Test Set-Up.....14
- 4.3 Limit.....15
- 4.4 Test Procedure.....15
- 4.5 Test Specification.....15
- 4.6 Test Result.....15
- 5 Power Harmonic and Voltage Fluctuation**
- 5.1 Power Harmonic and voltage Fluctuation test Equipment List.....16
- 5.2 Test Set-Up.....16
- 5.3 Limit.....16
- 5.4 Test Procedure.....17
- 5.5 Test Specification.....17
- 5.6 Test Result.....17
- 6 Electrostatic Discharge (ESD)**
- 6.1 Test Equipment List.....18
- 6.2 Test Set-Up.....18
- 6.3 Test Level.....18
- 6.4 Test Procedure.....19
- 6.5 Test Specification.....19
- 6.6 Test Result.....19
- 7 Radiated Susceptibility (RS)**
- 7.1 Test Equipment List.....20
- 7.2 Test Set-Up.....20
- 7.3 Test Level.....20
- 7.4 Test Procedure.....21
- 7.5 Test Specification.....21
- 7.6 Test Result.....21

**8 Electrical Fast Transient/Burst**

8.1 Test Equipment List.....22

8.2 Test Set-Up.....22

8.3 Test Level.....22

8.4 Test Procedure.....23

8.5 Test Specification.....23

8.6 Test Result.....23

**9 Surge**

9.1 Test Equipment List.....24

9.2 Test Set-Up.....24

9.3 Test Level.....24

9.4 Test Procedure.....25

9.5 Test Specification.....25

9.6 Test Result.....25

**10 Conducted Susceptibility**

10.1 Test Equipment List.....26

10.2 Test Set-Up.....26

10.3 Test Level.....26

10.4 Test Procedure.....27

10.5 Test Specification.....27

10.6 Test Result.....27

**11 Power Frequency Magnetic Field**

11.1 Test Equipment List.....28

11.2 Test Set-Up.....28

11.3 Test Level.....28

11.4 Test Procedure.....29

11.5 Test Specification.....29

11.6 Test Result.....29

**12 Voltage DIPS and Interruption Measurement**

12.1 Test Equipment List.....30

12.2 Test Set-Up.....30

12.3 Test Level.....30

12.4 Test Procedure.....31

12.5 Test Specification.....31

12.6 Test Result.....31

**13 Modification List**

**14 Appendix**

    Appendix A: Summary of Test Result.....34

    Appendix B: The Photograph of measurement.....48

    Appendix C: The Detail Photograph of EUT.....55

# 1. General Information

## 1.1 EUT Description

Applicant	: Advantech Co., Ltd.
Address	: Fl.4, No. 108-3, Ming-Chuan Road, Shing-Tien City, Taipei, Taiwan, R.O.C.
Equipment	: 5U-high Rackmount Chassis w/ backplane and power supply
Model	: CT-500 Series
Device's Class	: Class A Device
Operation Voltage	: 230VAC, 50Hz
Output Ports	:
Serial#1 port	: The serial#1 port is connected with one external modem, via one RS-232 cable which data cable is 180cm long, non-shielded, no ferrite bead.
Serial#2 port	: The serial#2 port is connected with one RS-232 cable, 180 cm long, non-shielded, no ferrite bead.
Parallel port	: Connected with one printer which data cable is 1.8 meters long, shielded, no ferrite bead.
Monitor port	: Connected with one monitor which data cable is 1.8 meters long, shielded, with ferrite bead.
USB#1~#3 ports	: The three USB ports are each connected with one USB mouse which data cable is 120 cm long, shielded, no ferrite bead.
USB#4 port	: The USB#4 port is connected with one USB cable, 120 cm long, non-shielded, no ferrite bead.
PS/2 mouse port	: Connected with one PS/2 mouse which length is 120 cm long, non-shielded, no ferrite bead.
PS/2 keyboard port	: Connected with one PS/2 keyboard which length is 120 cm long, non-shielded, no ferrite bead.
Power#1, #2 ports	: The two power ports are each connected with one power cable which cable length is 180 cm long, non-shielded, no ferrite bead, to the AC power source.

## 1.2 Test System Detail

**Monitor : HITACHI**

Model No. : CM771U  
Serial No. : V0E001074  
FCC ID : DoC Approval  
BSMI : 3882A707  
Power Type : 100-240VAC, 50/60Hz, 1.5A, Switching  
Power Cord : 180cm long, non-shielded, no ferrite bead.  
Data Cable : 120cm long, shielded, with ferrite bead  
Backshell : Metal  
Connected Port : VGA Port

**Keyboard : Logitech**

Model No. : SK-720  
Serial No. : N/A  
FCC ID : GYUR49SK  
BSMI : 3872A806  
Power Type : By PC  
Data Cable : 180cm long, shielded, no ferrite bead  
Backshell : Metal  
Connected Port : PS/2 Keyboard Port

**Mouse : Logitech**

Model No. : M-S48a  
Serial No. : N/A  
FCC ID : JNZ201213  
BSMI : 4882A001  
Power Type : By PC  
Data Cable : 120cm long, non-shielded, no ferrite bead  
Backshell : Metal  
Connected Port : PS/2 Mouse Port

**USB Mouse : Logitech**

Model No. : M-BB48  
Serial No. : LZE92250126  
FCC ID : DoC Approval  
BSMI : 4872A221  
Power Type : By PC  
Data Cable : 120cm long, shielded, no ferrite bead  
Backshell : Metal  
Connected Port : USB Port

**Modem : ACEEX**  
Model No. : XDM-9624  
Serial No. : 0017884  
FCC ID : IFAXDM-9624  
Power Type : 230VAC, 50Hz / 9VAC, 1A  
Power Core : 1.9meters long, non-shielded, no ferrite bead  
Data Cable : RS-232, shielded, 1.2meters long, no ferrite bead  
RJ11C x 2, 7' long, non-shielded, no ferrite bead  
Backshell : Metal  
Connected Port : Serial Port.

**Printer : Epson**  
Model No. : P950  
Serial No. : BW9Y113923  
FCC ID : DoC Approval  
BSMI : 3872P001  
Power Type : 230VAC, 50Hz, 0.4A  
Power Core : 165cm long, non-shielded, no ferrite bead  
Data Cable : 120cm long, shielded, no ferrite bead  
Backshell : Metal  
Connected Port : Parallel Port

**Hard disk driver : Seagate**  
Model No. : ST318406LC  
Serial No. : 3FE111EZ, 3FE13J98, 3FE110RB  
FCC ID : DoC Approval  
BSMI : 3902A781  
Power Type : 115/230VAC, 60/50Hz, 7/4A, Switching  
Power Cord : 26cm long, non-shielded, no ferrite bead.

**CPU : INTEL**  
Model No. : Pentium 3, 1000MHz  
Serial No. : Q220A64B-0040, Q220A64B-0041

**RAM : ELPIDA**  
Model No. : SD 256MHz  
Serial No. : PC-133 SD256M

**CD-ROM : QUANTA**  
Model No. : SCR-242  
Serial No. : PC006Q113500182  
FCC ID : DoC Approval  
BSMI : 3892A690  
Power Type : 115/230VAC, 60/50Hz, 7/4A, Switching  
Power Cord : 26cm long, non-shielded, no ferrite bead.

**Floppy disk driver : NEC**

Model No. : FD1238T  
Serial No. : EAHL096C1221  
FCC ID : DoC Approval  
Power Type : 115/230VAC, 60/50Hz, 7/4A, Switching  
Power Cord : 26cm long, non-shielded, no ferrite bead.

**Power : PRT**


Model No. : PRT300L  
Serial No. : 0264286, 0264287, 0264288, 0264289  
FCC ID : DoC Approval  
Power Type : 100/240VAC, 60/50Hz, 10/5.5A, Switching  
Power Cord : 40cm long, non-shielded, no ferrite bead.

### 1.3 EUT Configuration

- (1) The serial#1 port of EUT is connected with an external modem.
- (2) The serial#2 port of EUT is connected with a RS-232 cable.
- (3) The monitor port of EUT is connected with one monitor.
- (4) The USB#1~3 ports of EUT are each connected with one USB mouse.
- (5) The USB#4 port of EUT is connected with one USB cable.
- (6) The PS/2 keyboard port of EUT is connected with one PS/2 keyboard.
- (7) The PS/2 mouse port of EUT is connected with one PS/2 mouse.
- (8) The parallel port of EUT is connected with one printer.
- (9) The two power ports of EUT are each connected with the AC power source via one power cable.

(\*\*PS: Please refers to the Photograph\*\*)

#### Drawing of Configuration



## 1.4 EUT Exercise Software

The testing software is provided by the applicant.

It is designed to exercise the EUT in a manner similar to a typical use. The software will send an " H " pattern to the monitor and the " H " pattern will be shown on the monitor. The software will also send an " H " pattern to the printer and the " H " pattern will be printer out at the printer. The software will also send the data to the modem and the modem will response to the EUT. The HDD will continuously working sequence in the " Write-Read-Delete " mode. At the same time, the mouse and keyboard will be in continuously self-test mode and responded to the EUT. The software will enable all functions of EUT.

## 1.5 Test Performed

Conducted emissions were invested over the frequency range from 0.15MHz to 30MHz using a receiver which bandwidth is set at 9KHz.

Radiated emissions were invested over the frequency range from 30MHz to 1000MHz using a receiver which bandwidth is set at 120KHz. Radiated measurement was performed at distance that from an antenna to EUT is 10 meters.

The testing result of pretest was shown out that the "Transmitting/Receiving" mode is worse than the " Standby " mode. So, the final measurement was made on the "Transmitting/Receiving" mode.

There are three video resolution testing modes when the tests and the measurements was performed: "640 X 480 ", "1024 X 768 ", "1600 X 1200 " .

The testing result of pretest was shown out that the "1600 X 1200" mode is worse than other modes. So, the final measurement was made on the "1600 X 1200" mode.


## 2 Conducted Emission Measurement at Mains Port

### 2.1 Test Equipment

No.	Instrument	Manufacture	Model	Serial No.	Last Calibrate
1.	LISN (EUT)	Rolf Heine	NNB-2/16Z	99084	May 14, 2002
2.	LISN (AXE)	Rolf Heine	NNB-2/16Z	99086	May 14, 2002
3.	EMI Receiver	Rohde & Schwarz	ESI 7	830154/001	June 27, 2002
4.	50Ω Terminator	Amphenol	46650-51	N/A	Dec. 10, 2001
5.	RF Cable	Belden	M17/158	MIL-C-17	Jan. 20, 2002

Remark: All equipment upon which need to calibrated are with calibration period of one year.

### 2.2 Test Set-Up



### 2.3 Limit

Frequency	Limit (dBμV)			
	Class A		Class B	
	Quasi Peak	Average	Quasi Peak	Average
0.15 ~ 0.50	79	66	66 ~ 56	56 ~ 46
0.50 ~ 5.0	73	60	56	46
5.0 ~ 30.0	73	60	60	50

Remark: In the above table, the tighter limit applies at the band edges.

## 2.4 Test Procedure

The EUT and simulators are connected to the main power through a line impedance stabilization network (LISN). It provides a 50 ohm / 50  $\mu$ H coupling impedance for the measuring equipment. The peripheral devices are also connected to the main power through a LISN that provides a 50 ohm / 50  $\mu$ H coupling impedance with 50 ohm termination. (Please refers to the block diagram of the test setup and photograph.)

Both sides of DC line are checked for the maximum conducted emission interference. In order to find the maximum emissions, the relating positions of equipment and all of the interference cables must be changed according to EN 55011/1999 regulation: The measurement procedure on conducted emission interference.

The resolution bandwidth of the field strength meter ( Rohde & Schwarz ) is set at 9KHz.

## 5 Test Specification

According to the EN 55011/1999

## 2.6 Test Result

The emissions that come from the EUT were below the specified limits. The worst case of conducted emissions measurement are shown in the appendix A. The acceptance criterion was met and the EUT has pass the measurement.

## 2.7 Deviation from the Test Method

No Deviation.


### 3 Conducted Emission Measurement at Telecommunication Port

#### 3.1 Test Equipment

No.	Instrument	Manufacture	Model	Serial No.	Last Calibrate
1.	ISN (EUT)	Shaffner	ISN T411	200102-010	Feb. 24, 2002
2.	ISN Adapter	Shaffner	ADS T444	200102-032	Feb. 24, 2002
3.	EMI Receiver	Rohde & Schwarz	ESI 7	830154/001	Nov 22, 2001
4.	50Ω Terminator	Amphenol	46650-51	N/A	Dec. 10, 2001
5.	RF Cable	Belden	M17/158	MIL-C-17	Jan. 20, 2002

Remark: All equipment upon which need to calibrated are with calibration period of one year.

#### 3.2 Test Set-Up



#### 3.3 Limit

Class A ITE

Frequency	Limit (dBμV)		Limit (dBμA)	
	Voltage Limits		Currents Limits	
MHz	Quasi Peak	Average	Quasi Peak	Average
0.15 ~ 0.50	97 ~ 87	84 ~ 74	53 ~ 43	40 ~ 30
0.50 ~ 5.0	87	74	43	30
5.0 ~ 30.0	87	74	43	30

Remark: In the above table, the tighter limit applies at the band edges.

## Class B ITE

Frequency	Limit (dB $\mu$ V)		Limit (dB $\mu$ A)	
	Voltage Limits		Currents Limits	
MHz	Quasi Peak	Average	Quasi Peak	Average
0.15 ~ 0.50	84 ~ 74	74 ~ 64	40 ~ 30	30 ~ 20
0.50 ~ 5.0	74	64	30	20
5.0 ~ 30.0	74	64	30	20

Remark: In the above table, the tighter limit applies at the band edges.

### 3.4 Test Procedure

The characteristics of LCL of ISN:

150KHz ~ 1.5MHz: 80dB  $\pm$  3dB

1.5MHz ~ 30MHz: (80dB to 55dB)  $\pm$  3dB, decreasing linearly with the logarithm of the frequency

The ISN is connected to the communication port through a cable. The common-mode terminating impedance of this ISN observed from the communication ports when the disturbance is measured shall apply with the regulation. The ISN shall be inserted between the EUT and the auxiliary equipment that is required for operation of the EUT through the signal cable

Two sides of telecommunication ports are checked for the maximum conducted emission interference. In order to find the maximum emissions, the relating positions of equipment and all of the interference cables must be changed according to EN 55011/1999 regulation: The measurement procedure on conducted emission interference.

### 3.5 Test Specification

According to the EN 55011/1999

### 3.6 Test Result

N / A

### 3.7 Deviation from the Test Method

N / A


## 4. Radiated Emission Measurement

### 4.1 Test Equipment List

No.	Instrument	Manufacture	Model	Serial No.	Last Calibrate
11.	Antenna	Mess-Elektronik	VULB 9160	9160-3078	Jan. 19, 2002
2.	EMI Receiver	Rohde & Schwarz	ESI 7	830154/001	June 27, 2002
3.	RF Cable	Adventest	AD-N-CA-01	2000-0220	Jan. 20, 2002
4.	OATS	Bestlab	N/A	OATS#1	May 28, 2002

Remark: All equipment upon which need to calibrated are with calibration period of one year.

### 4.2 Test Setup



### 4.3 Limit

Frequency MHz	Class A		Class B	
	Distance (Meter)	Limit (dB $\mu$ V/m)	Distance (Meter)	Limit (dB $\mu$ V/m)
30 ~ 230	10	40	10	30
230 ~ 1000	10	47	10	37

Remark: In the above table, the tighter limit applies at the band edges

### 4.4 Test Procedure

The EUT and its simulators are placed on turn table, non-ducted and wooden, which is 0.8 meter above ground. The turn table rotates 360 degree to determine the position of the maximum emission level. The EUT was positioned such that distance from antenna to the EUT is 10 meters.

The antenna is moved up and down between 1 meter to 4 meter to receive the maximum emission level.

Both horizontal and vertical polarization of the antenna are set on measurement. In order to find the maximum emission, all of the interference cables must be manipulated according to EN 55011/1999 regulation: the test procedure of the radiated emission measurement.

The bandwidth set on the field strength is 120KHz when the frequency range is below 1GHz

### 4.5 Test Specification

According to EN 55011/1999

### 4.6 Test Result

The emissions that come from the EUT was below the specified limits. The worst case of conducted emissions measurement are shown in the appendix A. The acceptance criterion was met and the EUT has pass the measurement.

### 4.7 Deviation from the Test Method

No Deviation.


## 5. Power Harmonic and Voltage Fluctuation Measurement

### 5.1 Power Harmonic and Voltage Fluctuation Test Equipment List

No.	Instrument	Manufacture	Model	Serial No.	Last Calibrate
1.	H/F Test System	EMC Partner	Harmonic-1000	325807	May. 10, 2002

Remark: All equipment upon which need to calibrated are with calibration period of 1 year.

### 5.2 Test Setup



### 5.3 Limit of Harmonic Current

Limit of Harmonic Currents

Harmonic Order	Maximum Permissible Harmonic Current (Ampere)	Harmonic Order	Maximum Permissible Harmonic Current (Ampere)
Odd Harmonic		Even Harmonic	
3	2.30	2	1.08
5	1.14	4	0.43
7	0.77	6	0.30
9	0.40	8 ≤ n ≤ 40	0.23 x 8/n
11	0.33		
13	0.21		
15 ≤ n ≤ 39	0.15 x 15/n		

## 5.4 Test Procedure

The EUT is supplied in series with power analyzer from a power source has the same normal voltage and frequency as the rated supply voltage and the equipment under test. The rated voltage at the supply voltage of EUT of 0.94 times and 1.06 times shall be performed.

## 5.5 Test Specification

According to EN 61000-3-2/2000, EN 61000-3-3/1995

## 5.6 Test Result

N / A


## 6 .Electrostatic Discharge (ESD)

### 6.1 Test Equipment List

No.	Instrument	Manufacture	Model	Serial No.	Last Calibrate
1.	ESD Emulator	Noiseken	ESS-100L	0199C02380	Mar. 02, 2002

Remark: All equipment upon which need to calibrated are with calibration period of one year.

### 6.2 Test Setup



### 6.3 Test Level

Item	Environment	Unit	Test Specification	Performance Criteria
Enclosure Room	Electrostatic Discharge	KV(Charge Voltage)	8 (Air Discharge) 4 (Contact Discharge)	B

## 6.4 Test Procedure

Direct applicant of discharge to the EUT:

Contact discharge was applied only to the conducted surfaces of the EUT.

Air discharge was applied only to the non-conductive surfaces of the EUT.

When the measurement was taken, The ESD discharger was performed in single discharge. For the single discharge time between successive single discharges will keep on one second. It was at least ten single discharges with positive and negative at the same selected pointed. The selected pointed, which was performed with electrostatic discharge, was marked on the red label on the EUT.

Indirect applicant of discharge to the EUT:

Vertical Coupling Plane (VCP)

The coupling plane, of dimensions 0.5m x 0.5m, is placed parallel to , and positioned at a distance 0.1m from, the EUT, with the discharge electrode touching the coupling plane.

The four faces of the EUT will be performed with electrostatic discharge. It was at least ten single discharges with positive and negative at the same selected point.

Horizontal Coupling Plane (HCP)

The coupling plane is placed under the EUT. The generator shall be positioned vertically at a distance of 0.1m from the EUT, with the discharge electrode touching the coupling.

The four faces of the EUT will be performed with electrostatic discharge. It was at least ten single discharges with positive and negative at the same selected pointed.

## 6.5 Test Specification

According to EN 61000-4-2/1998

## 6.6 Test Result

The measurement of the electrostatic discharge was investigated and the test result was shown on the Appendix A. The acceptance criterion was met and the EUT has passed the measurement.


## 7. Radiated Susceptibility (RS)

### 7.1 Test Equipment List

No.	Instrument	Manufacture	Model	Serial No.	Last Calibrate
1.	Signal Generator	Rohde & Schwarz	SMY 02	845069/018	May 02, 2002
2.	Amplifier	Amplifier Research	100W1000M1A	20638	May 01, 2002
3.	Field Monitor	Amplifier Research	FM 2000	20391	Mar 03, 2002

Remark: All equipment upon which need to calibrated are with calibration period of one and half year.

### 7.2 Test Setup



### 7.3 Test Level

Item	Environment	Unit	Test Specification	Performance Criteria
Enclosure Room				
	Radio –Frequency	MHz	80 ~ 1000	A
	Electromagnetic Field	V/m (unmodulated, rms)	10	
	Amplitude Modulated	%AM (1KHz)	80	

## 7.4 Test Procedure

The EUT and load, which are placed on a wooden table that the height is 0.8 meter above ground, are placed with one coincident with the calibration plane such that the distance from antenna to the EUT is 3 meters.

Both horizontal and vertical polarization of the antenna position and four sides of the EUT are set on measurement.

In order to judge the EUT performance, a CCD camera is used to monitor the situation of EUT. All the scanning conditions are as follows:

Condition of Test	Remarks
EN 61000-4-3/1998	
1. Field Strength	10V/M; Level 3
2. Radiated Signal	AM 80% modulated with 1KHz
3. Scanning Frequencies	80MHz ~ 1000MHz
4. Dwell Time	3 seconds
5. Frequency step size $\Delta f$	1%
6. The rate of swept of frequency	$1.5 \times 10^{-3}$ decades/s

## 7.5 Specification

According to EN 61000-4-3/1998

## 7.6 Test Result

The measurement of the radiated susceptibility was investigated and the test result was shown on the appendix A. The acceptance criterion was met and the EUT has passed the measurement.


## 8 Electrical Fast Transient/Burst (EFT/B)

### 8.1 Test Equipment List

No.	Instrument	Manufacture	Model	Serial No.	Last Calibrate
1.	EMC Test System	EMC Partner	Transient-1000	TR1000-341	Aug 15, 2002
2.	Absorbing Clamp	EMC Partner	Transient-1000	CNEFT1000-176	Aug 15, 2002

Remark: All equipment upon which need to calibrated are with calibration period of one year.

### 8.2 Test Setup



### 8.3 Test Level

Item	Environment	Unit	Test Specification	Performance Criteria
Ports for signal Lines and Control Lines				B
	Fast Transients Common Mode	KV (Peak)	1	
		Tr/Ts (ns)	5/50	
		Rep. Frequency (KHz)	5	
DC Input and DC Output Power Ports				B
	Fast Transients Common Mode	KV (Peak)	2	
		Tr/Ts (ns)	5/50	
		Rep. Frequency (KHz)	5	
Input and Output AC Power Ports				B
	Fast Transients Common Mode	KV (Peak)	2	
		Tr/Ts (ns)	5/50	
		Rep. Frequency (KHz)	5	
Functional Earth Ports				B
	Fast Transients Common Mode	KV (Peak)	1	
		Tr/Ts (ns)	5/50	
		Rep. Frequency (KHz)	5	

## 8.4 Test Procedure

The EUT and load are placed on a wooden table that is 0.8meter height above a metal ground plane dimension is 1m x 1m and thickness is at least 0.2mm. It also projected beyond the EUT by at lease 0.1meter on all sides.

For Input and Output AC power or DC Input and DC Output Power Ports:

The EUT is connected with the power mains through a coupling device that directly couples the EFT interference signal.

Each of the line and nature conductors is impressed with burst noise for 1 minute.  
For Functional Earth Port:

The EUT is connected to the power mains through a coupling device that directly couples the EFT interference signal.

The protective earth line (PE) is impressed with burst noise for 1 minute.

The length of power cord between the coupling device and the EUT shall be 1 meter.  
For signal Lines and Control Lines Test:

The EFT interference signal is through a coupling clamp device couples to the signal and control lines of the EUT with burst noise for 1 minute.

## 8.5 Test Specification

According to EN 61000-4-4/1995

## 8.6 Test Result

The measurement of the Electrical Fast Transient/Burst was investigated and test result was shown on the appendix A. The acceptance criterion was met and the EUT has passed the measurement.


## 9. Surge

### 9.1 Test Equipment List

No	Instrument	Manufacture	Model	Serial No.	Last Calibrate
1.	EMC Test System	EMC Partner	Transient-1000	TR1000-341	Aug 15, 2002

Remark: All equipment upon which need to calibrated are with calibration period of one year.

### 9.2 Test Setup



### 9.3 Test Level

Item	Environment	Unit	Test Specification	Performance Criteria
<b>Dc Input and DC Output Power Ports</b>				
	Surge	Tr/Ts ( $\mu$ s)	1.2/50(8/20)	B
	Line to Ground	KV	$\pm 0.5$	
	Line to Line	KV	$\pm 0.5$	
<b>AC Input and AC Output Power Ports</b>				
	Surge	Tr/Ts ( $\mu$ s)	1.2/50(8/20)	B
	Line to Ground	KV	$\pm 4$	
	Line to Line	KV	$\pm 2$	

## 9.4 Test Procedure

The EUT and its load are placed on a table which is 0.8 meter height above a metal ground plane dimension is 1 meter x 1 meter and the thickness is 0.5 mm. It's also projected beyond the EUT at least 0.1 meter on all sides. The length of power cord between the coupling device and the EUT shall be 2meter or less.

For Input and Output AC Power or DC Input and Dc Output Power Ports:

The EUT is connected to the power mains through a coupling device that directly couples the Surge interference signal.

The Surge noise shall be applied synchronized to the voltage phase at 0°, 90°, 180°, 270° and the peak value of the AC voltage wave. (Positive and Negative)

Each of line-earth and line-line is impressed with a sequence of five surge voltages with interval of 1 minute.

## 9.5 Test Specification

According to EN 61000-4-5/1995

## 9.6 Test Result

The Measurement of the Surge was investigated and the test result was shown on the appendix A. The acceptance criterion was met and the EUT has passed the test.


## 10. Conducted Susceptibility

### 10.1 Test Equipment List

No.	Instrument	Manufacture	Model	Serial No.	Last Calibrate
1.	Signal Generator	Rohde & Schwarz	SMY 02	845069/018	May 02, 2002
2.	Power Amplifier	Amplifier Research	100W1000M1A	20638	May 01, 2002
4.	Directional Coupler	Amplifier Research	DC2600	20508	Aug 23, 2001
5.	CDN	FCC	FCC-801-M3-25A	9993	Aug 23, 2001

Remark: All equipment upon which need to calibrated are with calibration period of one year.

### 10.2 Test Setup



### 10.3 Test Level

Item	Environment	Unit	Test Specification	Performance Criteria
Ports for Signal Lines and Data Buses, not involved in process control, etc.				
	Radio-Frequency	MHz		0.15 ~ 80
	Common Mode	V (rms, Unmodulated)		10
	Amplitude Modulated	%AM (1KHz)		80
		Source Impedance		150
Ac Input and AC Output and DC Input and DC output Ports and Functional Earth Ports				
	Radio-Frequency	MHz		0.15 ~ 80
	Common Mode	V (rms, Unmodulated)		10
	Amplitude Modulated	%AM (1KHz)		80
		Source Impedance		150

## 10.4 Test Procedure

The EUT are placed on a table which is 0.8meter height and a ground reference plane on the table, the EUT are placed upon table and use a 10cm insulation between the EUT and ground reference plane.

For AC Input and AC Output Power or DC Input and DC Output Power Ports:  
The EUT is connected to the power mains through a coupling and decoupling networks for power supply lines. It also directly couples the disturbance signal into EUT.  
Use CDN-M2 for two wires or CDN-3 for three wires.

For Signal Lines Lines and Control Lines Test:  
The disturbance signal is through a coupling and decoupling networks (CDN) or EM-clamp device couples to the signal and control lines of the EUT.

All scanning frequencies conditions are as following:

Condition of Test	Remarks:
1. Field Strength	10V, Level 3
2. Radiated Signal	AM 80% modulated with 1KHz
3. Scanning frequencies	0.15MHz ~ 80MHz
4. Dwell Time	3 seconds
5. Frequency step size $\Delta f$	1%
6. The rate of Swept of Frequency	$1.5 \times 10^{-3}$ decades/s

## 10.5 Test Specification

According to EN 61000-4-6/1996

## 10.6 Test Result

The Measurement of the Conducted Susceptibility was investigated and the test result was shown on the appendix A. The acceptance criterion was met and the EUT has passed the test.


## 11 Power Frequency Magnetic Field

### 11.1 Test Equipment List

No.	Instrument	Manufacture	Model	Serial No.	Last Calibrate
1.	EMC Test System	EMC Partner	Transient-1000	TR1000-341	Aug 15, 2002
2.	Magnetic Coil	EMC Partner	MF-1000	MF1000-1-51	Aug 15, 2002

Remark: All equipment upon which need to calibrated are with calibration period of one year.

### 11.2 Test Setup



### 11.3 Test Level

Item	Environment	Unit	Test Specification	Performance Criteria
Enclosure Room				
Power-Frequency		50	Hz	A
Magnetic Field		30	A/M	

## 11.4 Test Procedure

The EUT and its load are placed on a table that is 0.8 meter above the metal ground plane dimension is at least 1 meter x 1 meter. The test magnetic field shall be placed at least than 3 meters distance from the induction coil.

The test magnetic field shall be applied by the immersion method to the EUT. The induction coil shall be rotated by 90° in order to expose the EUT to the test field with different orientation (X, Y, Z orientation).

## 11.5 Test Specification

According to EN 61000-4-8/1993

## 11.6 Test Result

The Measurement of the Power Frequency Magnetic Field was investigated and the test result was shown on the appendix A. The acceptance criterion was met and the EUT has passed the test.


## 12. Voltage Dips and Interruption Measurement

### 12.1 Test Equipment List

No.	Instrument	Manufacture	Model	Serial No.	Last Calibrate
1.	EMC Test System	EMC Partner	Transient-1000	TR1000-341	Aug 15, 2002

Remark: All equipment upon which need to calibrated are with calibration period of one year.

### 12.2 Test setup



### 12.3 Test Level

Item	Environment	Unit	Test Specification	Performance Criteria
Ac Input and AC Output Power Ports				
Voltage Dips		30	% Reduction	B
		10	ms	
		60	% reduction	C
		100	ms	
		>95%	Reduction	C
Voltage Interruption		5000	ms	

## 12.4 Test Procedure

The EUT and its load are placed on a wooden table which is 0.8 meter above a metal ground plane which dimension is 1 meter x 1 meter, the thickness is 0.65mm. It projected beyond the EUT by at least 0.1 meter on all sides. The power cord shall be used the shortest power cord as specified by the manufacturer.

For Voltage Dips / Interruption Test:

The EUT is connected to the power mains through a coupling device that directly couples to the Voltage Dips and Interruption Generator.

The EUT shall be tested for 30% voltage dips of supplied voltage and duration time is 10ms, for 60% voltage dips of supplied voltage and duration time is 100ms with a sequence of three voltage dips with intervals of 10 seconds, and for 95% voltage interruption of supplied voltage and the duration time is 5000ms with a sequence of three voltage interruptions with intervals of 10 seconds.

Voltage phase shifting are shall occur at 0°, 45°, 90°, 135°, 180°, 225°, 270°, 315° of the voltage.

## 12.5 Test Specification

According to EN 61000-4-11/1994

## 12.6 Test Result

N / A

## **13 Modification List for EMC Complying Test**

The modification is solely made by the applicant.

## **14 Appendix**

Appendix A: Summary of Test Result

Appendix B: The test photograph of EUT

Appendix C: The Detail Photograph of EUT

## Appendix A: Summary of Test Result

The test result in the emission and immunity were performed according to the requirement of measurement standard and procedures. Best Laboratory is assumed full responsibility for the accuracy and completeness of these measurements. The Test data of the emissions and immunity are listed as the appendix data.

All these tests are were carried out with the EUT in normal operation, which was defined as:

**\*\*\*\*\* EMC Test Result: The EUT has been passed the all measurements. \*\*\*\*\***

The uncertainty is calculated in accordance with NAMAS NIS 81, the total uncertainty for this test is as follows:

⇒ Emission Test

- \* Uncertainty in the Conducted Emission Test: <±2.0dB
- \* Uncertainty in the Field Strength measurement: <±4.0dB

### Conducted Emission Test

Date Measurement Performed: Aug. 22, 2002

EUT : 5U-high Rackmount Chassis w/ backplane and power supply

Testing Mode : 640 X 480

Temperature : 30°C

Humidity : 52%RH

**Line 1:**

Frequency (KHz)	Corrected Amplitude (dBµV)			Limit (dBµV)		Margin dB
	Peak	QP	Avg.	QP	Avg.	
167.0000	42.27	***	***	79.00	66.00	-23.73
291.1000	45.32	***	***	79.00	66.00	-20.68
330.2000	47.09	***	***	79.00	66.00	-18.91
343.8000	49.23	***	***	79.00	66.00	-16.77
376.1000	55.42	***	***	79.00	66.00	-10.58
451.7500	53.25	***	***	79.00	66.00	-12.75
611.5500	56.28	***	***	73.00	60.00	-3.72
719.5000	43.66	***	***	73.00	60.00	-16.34
1070.0000	43.45	***	***	73.00	60.00	-16.55
4535.0000	49.95	***	***	73.00	60.00	-10.05

**Line 2:**

Frequency (KHz)	Corrected Amplitude (dBµV)			Limit (dBµV)		Margin dB
	Peak	QP	Avg.	QP	Avg.	
167.0000	46.71	***	***	79.00	66.00	-19.29
284.3000	45.32	***	***	79.00	66.00	-20.68
321.7000	53.52	***	***	79.00	66.00	-12.48
429.6500	48.93	***	***	79.00	66.00	-17.07
462.8000	56.37	***	***	79.00	66.00	-9.63
601.3500	50.49	***	***	73.00	60.00	-9.51
750.1000	47.29	***	***	73.00	60.00	-12.71
1030.0000	44.05	***	***	73.00	60.00	-15.95
2870.0000	40.44	***	***	73.00	60.00	-19.56
4410.0000	55.65	***	***	73.00	60.00	-4.35

\*\*\* Remark: The above corrected amplitudes are all under the average limit. \*\*\*

### Conducted Emission Test

Date Measurement Performed: Aug. 22, 2002

EUT : 5U-high Rackmount Chassis w/ backplane and power supply

Testing Mode : 1024 X 768

Temperature : 30°C

Humidity : 52%RH

**Line 1:**

Frequency (KHz)	Corrected Amplitude (dBµV)			Limit (dBµV)		Margin dB
	Peak	QP	Avg.	QP	Avg.	
166.1500	42.83	***	***	79.00	66.00	-23.17
233.3000	41.37	***	***	79.00	66.00	-24.63
282.6000	44.37	***	***	79.00	66.00	-21.63
450.0500	47.35	***	***	79.00	66.00	-18.65
481.5000	47.70	***	***	79.00	66.00	-18.30
560.5500	44.30	***	***	73.00	60.00	-15.70
713.5500	42.56	***	***	73.00	60.00	-17.44
3080.0000	39.82	***	***	73.00	60.00	-20.18
4410.0000	47.84	***	***	73.00	60.00	-12.16
5230.0000	41.52	***	***	73.00	60.00	-18.48

**Line 2:**

Frequency (KHz)	Corrected Amplitude (dBµV)			Limit (dBµV)		Margin dB
	Peak	QP	Avg.	QP	Avg.	
169.5500	44.03	***	***	79.00	66.00	-21.97
296.2000	56.26	***	***	79.00	66.00	-9.74
391.4000	59.30	***	***	79.00	66.00	-6.70
711.0000	43.49	***	***	73.00	60.00	-16.51
908.2000	40.55	***	***	73.00	60.00	-19.45
1045.0000	43.04	***	***	73.00	60.00	-16.96
2650.0000	45.41	***	***	73.00	60.00	-14.59
2995.0000	45.46	***	***	73.00	60.00	-14.54
4685.0000	43.37	***	***	73.00	60.00	-16.63
5840.0000	41.88	***	***	73.00	60.00	-18.12

\*\*\* Remark: The above corrected amplitudes are all under the average limit. \*\*\*

### Conducted Emission Test

Date Measurement Performed: Aug. 22, 2002

EUT : 5U-high Rackmount Chassis w/ backplane and power supply

Testing Mode : 1600 X 1200

Temperature : 30°C

Humidity : 52%RH

**Line 1:**

Frequency (KHz)	Corrected Amplitude (dBµV)			Limit (dBµV)		Margin dB
	Peak	QP	Avg.	QP	Avg.	
155.9500	46.70	***	***	79.00	66.00	-19.30
253.7000	49.97	***	***	79.00	66.00	-16.03
347.2000	60.04	***	***	79.00	66.00	-5.96
360.8000	55.97	***	***	79.00	66.00	-10.03
399.9000	62.98	***	***	79.00	66.00	-3.02
496.8000	49.98	***	***	79.00	66.00	-16.02
616.6500	45.70	***	***	73.00	60.00	-14.30
705.9000	47.17	***	***	73.00	60.00	-12.83
2050.0000	38.49	***	***	73.00	60.00	-21.51
4950.0000	48.15	***	***	73.00	60.00	-11.85

**Line 2:**

Frequency (KHz)	Corrected Amplitude (dBµV)			Limit (dBµV)		Margin dB
	Peak	QP	Avg.	QP	Avg.	
166.1500	43.55	***	***	79.00	66.00	-22.45
233.3000	40.34	***	***	79.00	66.00	-25.66
287.7000	49.47	***	***	79.00	66.00	-16.53
367.6000	50.40	***	***	79.00	66.00	-15.60
385.4500	50.26	***	***	79.00	66.00	-15.74
435.6000	54.71	***	***	79.00	66.00	-11.29
742.4500	43.10	***	***	73.00	60.00	-16.90
2950.0000	41.74	***	***	73.00	60.00	-18.26
4550.0000	49.27	***	***	73.00	60.00	-10.73
5040.0000	43.66	***	***	73.00	60.00	-16.34

\*\*\* Remark: The above corrected amplitudes are all under the average limit. \*\*\*

## Field Strength Test

Date Measurement Performed: Aug. 14, 2002

EUT : 5U-high Rackmount Chassis w/ backplane and power supply

Testing Mode : 1600 X 1200

Polarity : Vertical

Temperature : 23°C

Humidity : 71%RH

Frequency (MHz)	Reading Amplitude (dBμV/m)	Table Degree (°)	Antenna Height (Meter)	Correction Factor (dB/m)	Corrected Amplitude (dBμV/m)	Limit (dBμV/m)	Margin (dB)
48.908	8.64	21	1.00	8.44	17.08	40.00	-22.92
66.382	17.02	174	1.00	6.47	23.49	40.00	-16.51
82.982	14.00	66	1.00	8.92	22.93	40.00	-17.07
427.234	9.24	169	1.00	17.55	26.79	47.00	-20.21
569.641	6.99	311	1.00	20.36	27.35	47.00	-19.65
***							

Remark:

1. The “ Correction Factor “ contains antenna factor, cable loss.
2. The formula of “ Corrected Amplitude “ is as follow”  
 Reading Amplitude + Correction Factor = Corrected Amplitude.

## Field Strength Measurement

Date Measurement Performed: Aug. 14, 2002

EUT : 5U-high Rackmount Chassis w/ backplane and power supply

Testing Mode : 1600 X 1200

Polarity : Horizontal

Temperature : 24°C

Humidity : 52%RH

Frequency (MHz)	Reading Amplitude (dBμV/m)	Table Degree (°)	Antenna Height (Meter)	Correction Factor (dB/m)	Corrected Amplitude (dBμV/m)	Limit (dBμV/m)	Margin (dB)
66.446	14.04	100	2.00	6.48	20.52	40.00	-19.48
70.597	21.81	41	4.00	7.00	28.80	40.00	-11.20
83.046	14.42	320	4.00	8.93	23.36	40.00	-16.64
427.238	8.50	301	2.50	17.55	26.06	47.00	-20.94
569.645	10.05	326	3.50	20.36	30.41	47.00	-16.59
***							

### Remark:

1. The " Correction Factor " contains antenna factor, cable loss.
2. The formula of " Corrected Amplitude " is as follow"  
 Reading Amplitude + Correction Factor = Corrected Amplitude.

## Power Harmonic / Fluctuation Test

### Power Harmonic:

Operating Environment:

Temperature : 26°C  
 Humidity : 68%RH  
 Atmosphere : 1010mBar

Test Condition:

EUT Position : Table Top

Result:

Summary of the test result: Pass

### Fluctuation Test:

Test Frequency : 50Hz  
 Test Time : 10 min.  
 Test Voltage : 230VAC  
 Tshort : 5.0 min

EUT	Data	Limit	Result	Test Enable
Pst	0.001	1.00	Pass	True
Plt	0.001	0.65	Pass	True
dc %	0.00	3.00	Pass	True
dmax %	0.00	4.00	Pass	True
d(t) sec	0.00	0.20	Pass	True

#### Power Source Data

Source Pst max	0.022	0.400	Pass	True
% THD	0.02	3.00	Pass	True

## Electrostatic Discharge Test

Item	Amount of Discharge	Voltage	Required Criteria	Complied to Criteria	Results
Air Discharge	10	+2KV	B	B	Pass
	10	-2KV	B	B	Pass
	10	+4KV	B	B	Pass
	10	-4KV	B	B	Pass
	10	+8KV	B	B	Pass
	10	-8KV	B	B	Pass
Contact Discharge	25	+2KV	B	B	Pass
	25	-2KV	B	B	Pass
	25	-4KV	B	B	Pass
	25	-4KV	B	B	Pass
Indirect Discharge	25	+2KV	B	B	Pass
	25	-2KV	B	B	Pass
	25	+4KV	B	B	Pass
	25	-4KV	B	B	Pass

### Remark:

- Criteria A: Operation as intended during and after the measurement
- Criteria B: Operation as Intended after the test
- Criteria C: Malfunction during and after, need manual reset
- Criteria D: The sample is damaged

## Radiated Susceptibility

Frequency (MHz)	Position (Angle)	Polarity (H or V)	Field Strength (V/m)	Required Criteria	Complied Criteria	Result
80 ~ 1000	0	H	10	A	A	Pass
80 ~ 1000	0	V	10	A	A	Pass
80 ~ 1000	90	H	10	A	A	Pass
80 ~ 1000	90	V	10	A	A	Pass
80 ~ 1000	180	H	10	A	A	Pass
80 ~ 1000	180	V	10	A	A	Pass
80 ~ 1000	270	H	10	A	A	Pass
80 ~ 1000	270	V	10	A	A	Pass

Remark:

- Criteria A: Operation as intended during and after the measurement
- Criteria B: Operation as Intended after the test
- Criteria C: Malfunction during and after, need manual reset
- Criteria D: The sample is damaged

## Electrical Fast Transient / Burst

Inject Line	Polarity	Voltage (KV)	Inject Time (Second)	Inject Method	Required Criteria	Complied Criteria	Result
L	±	2KV	60	Direct	B	B	Pass
N	±	2KV	60	Direct	B	B	Pass
PE	±	2KV	60	Direct	B	B	Pass
L+N	±	2KV	60	Direct	B	B	Pass
L+PE	±	2KV	60	Direct	B	B	Pass
N+PE	±	2KV	60	Direct	B	B	Pass
L+N+PE	±	2KV	60	Direct	B	B	Pass

Remark:

- ( ) Criteria A: Operation as intended during and after the measurement
- ( X ) Criteria B: Operation as Intended after the test
- ( ) Criteria C: Malfunction during and after, need manual reset
- ( ) Criteria D: The sample is damaged

## Surge Test

Inject Line	Polarity	Angle	Voltage (KV)	Inject Time (Second)	Inject Method	Required Criteria	Complied Criteria	Result
L+N	±	0	0.5KV	60	Direct	B	B	Pass
L+N	±	90	0.5KV	60	Direct	B	B	Pass
L+N	±	180	0.5KV	60	Direct	B	B	Pass
L+N	±	270	0.5KV	60	Direct	B	B	Pass
L+N	±	0	1.0KV	60	Direct	B	B	Pass
L+N	±	90	1.0KV	60	Direct	B	B	Pass
L+N	±	180	1.0KV	60	Direct	B	B	Pass
L+N	±	270	1.0KV	60	Direct	B	B	Pass
L+PE	±	0	0.5KV	60	Direct	B	B	Pass
L+PE	±	90	0.5KV	60	Direct	B	B	Pass
L+PE	±	180	0.5KV	60	Direct	B	B	Pass
L+PE	±	270	0.5KV	60	Direct	B	B	Pass
L+PE	±	0	1.0KV	60	Direct	B	B	Pass
L+PE	±	90	1.0KV	60	Direct	B	B	Pass
L+PE	±	180	1.0KV	60	Direct	B	B	Pass
L+PE	±	270	1.0KV	60	Direct	B	B	Pass
L+PE	±	0	2.0KV	60	Direct	B	B	Pass
L+PE	±	90	2.0KV	60	Direct	B	B	Pass
L+PE	±	180	2.0KV	60	Direct	B	B	Pass
L+PE	±	270	2.0KV	60	Direct	B	B	Pass
N+PE	±	0	0.5KV	60	Direct	B	B	Pass
N+PE	±	90	0.5KV	60	Direct	B	B	Pass
N+PE	±	180	0.5KV	60	Direct	B	B	Pass
N+PE	±	270	0.5KV	60	Direct	B	B	Pass
N+PE	±	0	1.0KV	60	Direct	B	B	Pass
N+PE	±	90	1.0KV	60	Direct	B	B	Pass
N+PE	±	180	1.0KV	60	Direct	B	B	Pass
N+PE	±	270	1.0KV	60	Direct	B	B	Pass
N+PE	±	0	2.0KV	60	Direct	B	B	Pass
N+PE	±	90	2.0KV	60	Direct	B	B	Pass
N+PE	±	180	2.0KV	60	Direct	B	B	Pass
N+PE	±	270	2.0KV	60	Direct	B	B	Pass

### Remark:

- Criteria A: Operation as intended during and after the measurement
- Criteria B: Operation as Intended after the test
- Criteria C: Malfunction during and after, need manual reset
- Criteria D: The sample is damaged

## Conducted Susceptibility

Inject Line	Field Strength V	Inject Method	Required Criteria	Complied Criteria	Result
AC Line	10V	CDN	A	A	Pass

Remark:

- Criteria A: Operation as intended during and after the measurement
- Criteria B: Operation as Intended after the test
- Criteria C: Malfunction during and after, need manual reset
- Criteria D: The sample is damaged

## Power Frequency Magnetic Field Test

Polarization	Frequency (Hz)	Magnetic Strength (A/M)	Required Criteria	Complied Criteria	Result
X Orientation	50	30	A	A	Pass
Y Orientation	50	30	A	A	Pass
Z Orientation	50	30	A	A	Pass

Remark:

- Criteria A: Operation as intended during and after the measurement
- Criteria B: Operation as Intended after the test
- Criteria C: Malfunction during and after, need manual reset
- Criteria D: The sample is damaged

## Voltage Dips and Interruption Test

Voltage Dips and Interruption Reduction (%)	Angle (Degree)	Test Duration (ms)	Required Criteria	Complied Criteria	Result
<b>DIP</b>					
30	0	10	B	B	Pass
30	45	10	B	B	Pass
30	90	10	B	B	Pass
30	135	10	B	B	Pass
30	180	10	B	B	Pass
30	225	10	B	B	Pass
30	270	10	B	B	Pass
30	315	10	B	B	Pass
60	0	100	C	C	Pass
60	45	100	C	C	Pass
60	90	100	C	C	Pass
60	135	100	C	C	Pass
60	180	100	C	C	Pass
60	225	100	C	C	Pass
60	270	100	C	C	Pass
60	315	100	C	C	Pass
<b>Interruption</b>					
>95	0	5000	C	C	Pass
>95	45	5000	C	C	Pass
>95	90	5000	C	C	Pass
>95	135	5000	C	C	Pass
>95	180	5000	C	C	Pass
>95	225	5000	C	C	Pass
>95	270	5000	C	C	Pass
>95	315	5000	C	C	Pass

**Remark:**

- ( ) Criteria A: Operation as intended during and after the measurement
- ( X ) Criteria B: Operation as Intended after the test (Test Mode: 30%)
- ( X ) Criteria C: Malfunction during and after, need manual reset(Test Mode: 60%, >95%)
- ( ) Criteria D: The sample is damaged

## Appendix B: The Test Photograph of EUT

The Photograph of Conducted Emission Test --- Mains Port



### The Photograph of Radiated Emission Test



The Photograph of Radiation Susceptibility Test



The Photograph of Electrical Fast Transient/Burst Test



The Photograph of Electrostatic Discharge Test



### The Photograph of Surge Test



### The Photograph of Conducted Susceptibility Test



The Photograph of Power Frequency Magnetic Field Test




The Photograph of Voltage Dips and Interruption Test




## Appendix C: The Detail Photograph of EUT


















































**PRT**

MODEL: PRT300L  
SWITCHING POWER SUPPLY

DC OUTPUT	10V	20V	30V	40V	50V	60V	70V	80V	90V	100V
Output	+1.2V	+0.1	+0.0	-0.1	-0.2	-0.3	-0.4	-0.5	-0.6	-0.7
Current	2.0A	1.0A	0.5A	0.2A	0.1A	0.05A	0.02A	0.01A	0.005A	0.002A
Watt	+1.2A	+0.1A	+0.0A	-0.1A	-0.2A	-0.3A	-0.4A	-0.5A	-0.6A	-0.7A

**WARNING**  
Hazardous voltages contained within  
the power supply are used throughout  
return to service center for repair.

**ATTENTION**  
Tous les composants de cet alimentateur  
sont protégés par des dispositifs de sécurité.  
Remettre à l'usine pour réparation.

**WARNING**  
Hazardous voltages contained within  
the power supply are used throughout  
return to service center for repair.

**PELIGRO**  
Tous les composants de cet alimentateur  
sont protégés par des dispositifs de sécurité.  
Remettre à l'usine pour réparation.

LEVEL 1  
SOURCE  
MADE IN TAIWAN R.O.C.



06/25/02  
0264200

BT1